



# **Touch Panel Station 5**

The Pharos TPS 5 (Touch Panel Station 5") is an elegant interface with a customisable, 5" capacitive touchscreen, compatible with any Pharos Designer Controller.

The front panel is a seamless, uninterrupted glass plate available in Black and in White, giving an elegant touch experience, with improvements to its core functionality, touch performance, screen resolution, and vastly superior aesthetics. And, with a unique and innovative universal mounting solution, the TPS 5 will be easy to wall mount in your installation, regardless of region.



### **TPS 5 Features**



## **Touch Interface**

The 5" vivid colour capacitive touchscreen makes navigating your project's controls appealing and intuitive. It's quick and easy to activate presets, manual overrides, or use a custom colour picker to personalise your lighting. The TPS 5 puts control of the Pharos Designer system at your fingertips.



#### Customisable

Create your fully customisable user interface using the free Pharos Designer software. Create multiple pages of controls including buttons, sliders, keypads and colour pickers, and configure their appearance and visual feedback. Make it eye-catching by importing your own graphics or picking from one of our attractive themes, with support for extended character sets, such as Arabic, Chinese, Cyrillic, Japanese and Korean.



#### Touchscreen Hardware

The new and improved TPS 5 is designed using superior, up-to-date technology. The new screens have a high DPI, with a resolution of 800x480 in a 5" display. And, with updated technology, comes greater responsiveness with the interface, enabling five-point multi-touch, giving smooth transitions, higher screen fidelity and more processing power, allowing more pages to be loaded.



### Designer

Create interface pages in Pharos Designer 2 at the same time you programme the controller, and upload in one simple operation.



# Installation

The TPS 5 ships with a new, innovative wall-mounting system. The Universal Mounting plate can be fitted to a wide range of regulation backboxes, including UK, US and EU. The TPS 5 fits to the mounting plate via a bayonet twist system which is not immediately obvious to an observer. This keeps it securely fastened with a toolless installation, and the MicroSD card remains securely out of reach whilst installed.



## Scalable

Multiple Touch Devices can be combined with one or more Pharos Designer Controllers on the same network to build the ideal system for your installation, with a maximum of 40 Controllers and Touch Devices in total. Each Touch Device is easily programmed using our Designer software.



## Network

The TPS 5 requires any Pharos Designer Controller, and links to it using standard protocols over an Ethernet network.



## Power-over-Ethernet

As a Power-over-Ethernet (PoE) device, the TPS 5 can be placed at any remote location and only needs a single Ethernet cable that provides both power and data.





Ca		

Orientation Portrait or landscape Layouts Free editable layouts

**Pages** Any number of pages, although performance may be affected

by complexity and number

Convenient and custom navigation via configurable Navigation

navigation bars

**Fonts** Custom font support, including fonts with extended character

sets e.g. Arabic, Chinese, Cyrillic, Japanese and Korean

**Themes** Wide selection of themes available to download, or create

your own with Designer's theme editor

**Controls** A wide array of customisable buttons, sliders, colour pickers,

labels, keypads and clocks

**Flexible** Fully integrated with Designer Trigger, so button states,

Integration graphics, and captions can change according to any number of

preset triggers

**Secure Access** Keypad for PIN-code entry; multiple user levels **Commissioning** Commissioned with Pharos Designer 2.9 or later

# **Interfaces**

RJ45 socket for 10/100Base-TX Ethernet with Link/Data LEDs; **Ethernet** 

Static IP or DHCP

5" capacitive five-point multi-touch; 800×480 24bpp; Touchscreen

# **Specifications**

PoE (IEEE802.3af, Class 0), 7W typical **Power** Required Any Pharos Designer Controller Configuration Pharos Designer 2.9 or later **Data Storage** Removable MicroSD Card (supplied)

**Temperature** 0°C to 50°C (32°F to 122°F) Humidity 10-90% relative, non-condensing

Ingress IP40

**Physical** Wall mounted, partly recessed with a


custom mounting plate that supports UK 1 & 2-gang 35mm, EU 35mm or US 2.5" backbox (mounting plate included) 14 x 9.7 x 2.8 cm (5.5 x 3.8 x 1.1 in) 0.25 kg (0.6 lbs) (ex. mounting plate)

Shipping 19.5 x 15 x 7.5 cm (8 x 6 x 3 in)

0.5 kg (1.1 lbs)

Recovery Hardware watchdog and recessed

reset button



# Order Code & Variants

Designer Touch Panel Station 5" Black TPS 5 B (LCD) (Wall mount touchscreen interface)

TPS 5 W (IPS) Designer Touch Panel Station 5" White

(Wall mount touchscreen interface)

Pharos Universal Mounting Plate 5" included

If no colour is specified, TPS 5 B will be shipped by default

### Pharos Designer Controller required

### **Colour Information**

Jet Black Bayblend T65XF (UL94 HB) RAL 9005

jet black

**Signal White** Bayblend T65XF (UL94 HB) RAL 9003

signal white

# Warranty & Certifications

Warranty 5 years

Certifications CE compliant, UKCA compliant,

UL/cUL listed.









